

**Product Code:** CL052

**Description:** 13A Double Pole Switched Fused Connection Unit With Neon & Optional Flex Outlet



### General Information

|                                |  |   |
|--------------------------------|--|---|
| <b>Dimensions</b>              | 80mm (W) x 80mm (H) x 42mm (D)                               |   |
| <b>Finish</b>                  | Metal Clad Grey  |   |
| <b>Materials</b>               | Front Plate & Mounting Box: Electrophoretically Coated Steel | Insert, Switch, Fuse Drawer & Housing: Urea |
|                                | Neon Lens: Polycarbonate                                     | Terminals: Brass                            |
|                                | Terminal Screws: Steel & Yellow Passivated                   | Contacts: Silver "on-lay" Copper / Brass    |
|                                | Internal Busbars: Formed Pressed Brass                       | Earth Strap: Mild Steel                     |
| <b>Maximum Voltage</b>         | 250V~ 50Hz   |   |
| <b>Load Rating</b>             | 13A  |   |
| <b>Plate Fixing Centres</b>    | 60.3mm   |   |
| <b>Terminal Size</b>           | 5mmø   |   |
| <b>Terminal Torque</b>         | 2.0Nm  |   |
| <b>Terminal Capacity</b>       | 3 x 2.5mm <sup>2</sup> or 2 x 4mm <sup>2</sup>               |   |
| <b>Switched</b>                | Yes  |   |
| <b>Double Pole</b>             | Yes  |   |
| <b>Twin Earth Terminals</b>    | Yes  |   |
| <b>Neon Indicator</b>          | Yes (Red)  |   |
| <b>Fuse Fitted</b>             | 13A (BS 1362)  |   |
| <b>Flex Outlet</b>             | Yes (10mmø Through Front of the Plate)                       |   |
| <b>Back Box Depth</b>          | 40mm Supplied  |   |
| <b>Termination Type</b>        | Screw  |   |
| <b>Earth Terminal Provided</b> | Yes  |   |
| <b>Back Box Knockouts</b>      | 5 x 20mm (2 on top, 1 on bottom, 1 on each side)             |   |
| <b>Operational Temperature</b> | -5°C to +40°C  |   |
| <b>Warranty</b>                | 10 Years   |   |
| <b>Standards</b>               | BS 1363-4: 2016 +A1: 2018<br>BS 1362:1973                    |   |

### Additional Information

Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.  
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.