



INSTALLATION & MAINTENANCE MANUAL

OSPCR

GENERAL INSTRUCTIONS

These instructions should be read carefully and retained after installation by the end user for future reference and maintenance.

These instructions should be used to aid installation of the following product:

OSPCR

SAFETY

- This product must be installed in accordance with the latest edition of the IEE Wiring Regulations (BS7671) and current Building Regulations. If in any doubt, consult a qualified electrician
- Please isolate mains prior to installation or maintenance
- Please note the IP (Ingress Protection) rating of this product when deciding the location for installation
- Do not overload this accessory or subject it to conditions outside its rating
- This product is IP65 rated (IP20 from rear)

INSTALLATION

- Choose a suitable location for installation. Do not install the unit facing artificial or reflected light, this will cause the sensor to cycle on and off at night
- The product is designed to fit into a 17mm cut-out within a suitable IP rated enclosure, it cannot be installed independently
- Using the seals and lockrings supplied, place the sensor into the hole and fasten securely against the enclosure wall. The inner locking may be omitted and the outer locking tightened against the body of the sensor, but both seals should be used (see Fig. 1)




Fig. 1

- Connect as shown in Fig. 2




Fig. 2

- Switch on and check for correct operation
- There is a switching delay of 20-120 seconds after the ambient light level changes. It is normal for the sensor to take a few minutes to turn off when first installed
- To test, cover with opaque material, do not use fingers as light passing through fingers may be enough to keep the switch open

WARNING

This product must be disconnected from the circuit if subjected to any high voltage or insulation resistance testing. Irreparable damage will occur if this instruction is not followed.

GENERAL

This product should be recycled in the correct manner when it reaches the end of its life. Check local authorities for where facilities exist.

Clean the external surfaces with a damp cloth using a mild solution of detergent and warm water only, do not use aggressive cleaning products or solvents which may damage the product. Do not use any source of high-pressure washers to maintain or clean this product.

WARRANTY

This product has a warranty of 2 years from date of purchase. Failure to install this product in accordance with the current edition of the IEE Wiring Regulations (BS7671), improper use, or removal of the batch code will invalidate the warranty. If this product should fail within its warranty period, it should be returned to the place of purchase for a free of charge replacement. ML Accessories does not accept responsibility for any installation costs associated with the replacement product. Your statutory rights are not affected. ML Accessories reserve the right to alter product specification without prior notice.

230V
50Hz



IP65

ML
ACCESSORIES LTD



**UK
CA** **CE**



02

SUPPLIED BY:

(UK) MANUFACTURER
ML ACCESSORIES LTD,
UNIT E CHILTERN PARK,
BOSCOMBE ROAD,
DUNSTABLE
LU5 4LT,
[WWW.MLACCESSORIES.
CO.UK](http://WWW.MLACCESSORIES.CO.UK)

**(EU) AUTHORISED
REPRESENTATIVE**
SLV LIGHTING GROUP,
DAIMLERSTRASSE 21-23,
52531 ÜBACH-PALENBERG,
GERMANY
EMAIL: [EPREL@GROUP.SLV.
COM](mailto:EPREL@GROUP.SLV.COM)

MADE IN CHINA

DCDEC22_V1