

Apollo XP95 Multisensor Detector

Part No. **55000-885APO**



Overview

Fully compatible with C-TEC's XFP&ZFP XP95/Discovery Addressable Fire Panels.

Combines an optical smoke sensor and thermistor temperature sensor.

Responds well to a wide range of fires.

Well suited for environments such as hotel bedrooms.

Red LED illuminates when the detector is in alarm.

Certified to EN54-7 by the LPCB.

Requires a 45681-210APO standard base or 45681-242APO low power relay base.

'Xpert' card addressed for speedy installation.

Technical Specifications

Approvals/certifications	Certified to EN54-7 by the LPCB.
Compatibility	Compatible with C-TEC's XFP/ZFP XP95/Discovery Addressable Fire Panels.
Application/operation	Combines inputs from optical smoke and heat sensors and processes them using a sophisticated algorithm. Designed to be sensitive to a wide range of fires. Provides a good response to overheating/thermal combustion and to flaming fires with high heat.
Application temperature	TBC.
Static response temperature	TBC.
Supply wiring	2-wire, polarity insensitive.
Supply/operating voltage	17 to 28V DC.
Quiescent current	500µA average; 750µA peak.
Alarm current	2mA (LED illuminated).
Indicators	Clear LED emitting red light when in alarm.



Connections	L1&L2 supply in/out; +R remote LED +Ve connection; -R remote LED -Ve connection. (4mA remote LED current @ 5V measured across remote load).
Product dimensions (mm)	100mm diameter x 50 mm H (not in base). 58mm height when in base.
Construction & finish	White polycarbonate V.O rated rated to UL94. Stainless steel terminals.
IP Rating	IP43.
Weight	105g (not in base); 160g (in base).
Operating conditions/temperature	-20°C to +60°C.
Notes	Requires a BF308XP standard base or BF308XPR low power relay base. 1mA power up surge current for 0.3 seconds.



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom