

Product Code: CL840

Luckinslive 403357800

Description: 13A 2 Gang Double Pole Switched Socket Outlet With Outboard Rockers & Neons



General Information

Dimensions (mm)	140 (W) x 80 (H) x 42 (D)		
Plate Fixing Centres - Horizontal (mm)	120.6		
Style	Metal Clad		
Colour	Grey		
Insert Colour	White		
Materials	Front Plate & Mounting Box:		Insert: Urea
	Electrophoretically Coated Steel		Neon Lens: Polycarbonate
	Rear Housing: Urea		Terminal Screws: Steel & Yellow Passivated
	Terminals: Brass		Internal Busbars: Formed Pressed Brass
	Contacts: Silver "on-lay" Copper / Brass		
Earth Strap: Mild Steel			
Operating Voltage (AC)	250	Frequency (Hz)	50
Resistive Load Rating (A)	13		
Termination Type	Screw		
Terminal Size (mm)	Ø5	Terminal Torque Value (Nm)	2
Terminal Capacity - Solid (mm ²)	3 x 2.5 or 2 x 4		
Double Pole Switch	Yes		
Twin Earth Terminals	Yes		
Neon Indicator	Yes	Indicator Colour	Red
Supplied Back Box Depth (mm)	40		
Back Box Knockouts - Total (mm)	7 x Ø20		
Back Box Knockouts - Top (mm)	3 x Ø20	Back Box Knockouts - Bottom (mm)	2 x Ø20
Back Box Knockouts - Rear (mm)	None	Back Box Knockouts - Sides (mm)	1 x Ø20
Back Box Earth Terminal Supplied	Yes		
Ingress Protection	IP20		
Operational Temperature (°C)	-5 to +40		
Warranty (Years)	20		

Standards BS 1363-2

Additional Information

For cleaning / polishing of products, use only a soft, dry, clean cloth.
 Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.
 Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal.



CLICK OR SCAN

Catalogue



Range



DoC



Installation



CLICK OR SCAN