

Product data sheet

WRSSU83BSW

:hager



13A FCU Switched Brushed Steel White Insert

Technical Characteristics

| | |
|---------------|---|
| Switch mode | 3pole |
| Frequency | 45/65 Hz |
| Rated current | 13 A |
| Fuse | short-circuit proof |
| Depth | 30.3 mm |
| Height | 86 mm |
| Width | 86 mm |
| Colour | stone grey optics |
| Material | |
| Imprint | ekey card design imprint |
| Wiring | |
| Component | with 2 fixing screws M3.5 x 30 mm |
| Lighting | invisible, glare-free IR LED night lighting |
| Standard | BS EN 50083-2 |
| Protection | with sabotage protection by contact in cover and arcing contact |
| Insert | insert grey, mat |