



2 Way Booster with IR Bypass

watch and control your Sky™ box
in 2 additional rooms

Part Number:
27822BMR

Features & Benefits

- Distributes HD TV, Freeview, DAB and FM signals
- Single Input – for TV, DAB or FM signal
- 2 Outputs – suitable for up to 2 additional TVs/radios
- Integrated IR bypass compatible with Digi Eye remote control extenders
- 20dB Gain per port ideal for long cable runs or weak signals
- RED Compliant – updated to improve signal handling



Product Specifications

Frequency Range	87-230MHz (FM/DAB), 470-790MHz (TV Ch 21-60)
Noise Figure	Typ. <3dB
Isolation Between Outlets	12dB
Max Output Level	94dB μ v
IR Bypass	5-30MHz + 3dB
IR Power	9VDC 15mA SSP
Power Requirement	220-240V-50/60Hz, <3W

Product Information

EAN	5050171077689
Unit Quantity	1
Unit Dimensions	10.2cm x 25.8cm x 5.5cm
Unit Weight	249g
Outer Quantity	20
Outer Dimensions	42.5cm x 25cm x 31.5cm
Outer Gross Weight	7.39kg
Outer Net Weight	6.61kg

Distributed By



01234 26 37 37

sales@philex.com

www.philex.com