




**Product Description:** BatPac™ PRO 1200mm 22W Batten


Introducing BatPac™ PRO. This product provides over 40% energy savings compared to traditional fluorescent, however provides the direct replacements for single or twin fittings in size and output. Can also be surface mounted or suspended.

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour	SKU Type
EN-BA1222/40	22	4000	2800	128	120	White	Non Dimmable
EN-BA1222EM/40	22	4000	2800	128	120	White	Emergency
EN-BA1222EMMS/40	22	4000	2800	128	120	White	Emergency Microwave
EN-BA1222MS/40	22	4000	2800	128	120	White	Microwave


**Line Drawing**



**Polar Curve**



**Colour**



White


## Product Features:

- Opal polycarbonate diffuser
- Delivering 118lm/W
- Knockouts for cable entry on both ends
- IK08 rated impact resistance
- Push-fit terminals and clip-in gear tray for fast installation
- Multiple BESA mounting points (matches traditional fluorescent)
- Adjustable light detector from 2-50 lux for microwave option
- Adjustable hold time 5 secs to 30 mins for microwave option
- 5 year warranty

## Product Specs:

Input Voltage	220~240V AC	Input Frequency	50/60HZ
Power Factor	0.9	IP Rating	IP20
Lifetime L70 (hrs)	50000	IK Rating	IK08
Lamp Base	Other	Width (mm)	61
Length (mm)	1170	Weight (Kg)	1.539
Height (mm)	71	Product Type	Linears
Operating Temp. (Min) °C	-20°C	Operating Temp. (Max) °C	45°C

## Compliance & Approvals:



## Warranty:

This product has a warranty period of 5 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase. The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.