AURORA®
VALUE BEYOND ILLUMINATION™

LEDline™ PROCX

make smart with AOne control | requires .hub | works with .control | CX | 16A

Product Description: LEDLine™ PROCX 9.6W CRI90 Tuneable White LED Strip

24V Tuneable White CRI90 LED strip is suitable for use in applications where a range of colour temperatures may be required. The tuneable white feature allows the strip to adjust colour temperature between 2500-6000K. With a beam angle of 120° individual light points are less visible creating a continuous glow, delivering up to 750lm per metre. Strip is ideal for use with the AOne™ AU-A1ZBSCCX tuneable white strip controller & the app for further control. Wall controller option is also available. Strip can be cut to length and 2m leads soldered to special order. Reel length 30m.

SKU Code	Wattage	Colour	Lumens	Lumens/Watt	Beam Angle	Finish Colour
EN-ST90CX	9.6	2500-6000	450	47	120	White

Line Drawing



Polar Curve

Colour

Product Features:

- Compatible with the AOne™ app
- CRI90 flexible LED strip with 3M™ self adhesive backing
- CRI90 brings out the true colour of objects and surroundings
- Tuneable white colour temperature between 2500-6000K
- Cut points every 100mm for maximum flexibility
- Beam angle of 120° and 17mm between LEDs, 60 LEDs/m
- Maximum length of run 10m
- For runs over 10m lengths to be connected in parallel
- Requires 24V DC Constant Voltage LED driver
- Reel length 30m
- 3 Year Warranty

Product Specs:

Input Voltage	24~V DC
Lifetime L70 (hrs)	30000
Height (mm)	2
IP Rating	IP20
Width (mm)	10
Product Type	LED Strip

Compliance & Approvals:

Warranty:

This product has a warranty period of 3 Years. Warranties may be available on certain products as indicated in the product description. Warranties are valid from the date of purchase.The warranty is invalid in the case of improper use, installation, tampering, removal of the Q.C. date label or installation in an improper working environment or installation. Should this product fail during the warranty period it will be replaced free of charge, subject to the correct installation of the original product and subsequent return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product and Aurora reserves the right to alter specifications without prior notice.