



#### Overview

The Belum LED emergency exit sign is a self-contained, multi-purpose, maintained or non-maintained 3hour emergency solution. This wall mounted panel has LEDs along the under edge. May be used as a standard emergency luminaire without the exit sign graphic. Supplied with Upward arrow exit sign. Standard or Self-Test options







#### General Information

IP Rating	IP20
Protection	Class I
Rating	
Installation	Internal
Area	
UEM/EME	Class I
Protoction	





08201 BEL0105

# Belum EME exit sign 1W/5W 6500K

- Hidden slot at the frame for attaching exit sign film
- Available in self-test version
- Maintained and non-maintained options
- Emergency lights under the fitting illuminate the door way
- All legends included







Technical Summary			
Product Code	BEL0105		
Maximum Efficiency	70 lm/W		
Emergency Luminous Flux	70 lm		
Weight	0.57Kg		
Dimensions (L x W x D) (mm)	391x194x53		
UEM/EME Battery Life	4 y		
UEM/EME Input Voltage	220-240Vac 50/60Hz		
UEM/EME Ambient Temperature Range	0°C to 40°C		
UEM/EME Power Factor	0.57		
Emergency Modes	Maintained or Non-maintained		
UEM/EME Test Function	Manual		
UEM/EME CCT	6,500 K		
UEM/EME Input Power (Max)	5 W		
UEM/EME Protection	Class I		
UEM/EME Weight	1.08 kg		
UEM/EME Dimensions (L x W x D) (mm)	194x391x53		
UEM/EME Emergency Operation Test	Manual		

Tel: 01635 523 713

Email: sales@kosnic.com

Kosnic.com











Kosnic Lighting KosnicUK KosnicLightingUK KosnicUK





### Overview

The Belum LED emergency exit sign is a self-contained, multi-purpose, maintained or non-maintained 3-hour emergency solution. This wall mounted panel has LEDs along the under edge. May be used as a standard emergency luminaire without the exit sign graphic.

Supplied with Upward arrow exit sign. Standard or Self-Test options







## General Information

IP Rating	IP20	
Protection	Class I	
Rating		
Installation	Internal	
Area		
UEM/EME	Class I	
Protection		

Tel: 01635 523 713

Email: sales@kosnic.com

Kosnic.com











# Kosnic Lighting KosnicUK KosnicLightingUK KosnicUK

# Belum



08201 BEL0105

## Accessories

Product Code	Description	Туре
KBAT2600LI1	Li-ion Battery Pack, 2600mAh for self test versions of Manot, Mulu, Belum, Kalem, Nitro, Nitro surface, Doxa	Battery
KBAT2000LI1	Li-ion battery 3.7V 2000mAh for self test DD EME	Battery

