

EMERGENCY CONVERSION KIT 2.5W 20-90VDC 3HR WITH REMOTE LED INDICATOR AND MANUAL TEST BUTTON

ILEMPK011



Note: Warranty increased to 5 years on 27/03/2025

Details

Barcode: 5055788288862

Quick Order Code:165555Category:EmergencyRange Name:Conversion Kit

Product Type:Emergency Conversion KitProduct Body Finish:Matt white. End cap blue

Market Segment: Commercial indoor

Finish: Matt white. End cap blue

Warranty (Years): 5

Physical Data

Product Length (mm): 240
Product Depth (mm): 28
Product Width (mm): 50
Product Weight (g): 215

Material:PolycarbonateConstruction:Injection moulding

Bulb or Luminaire Shape: Rectangle Luminaire Fixing: In Ceiling

Placement / Application: Indoor, Emergency Lighting

Electrical Data

Power Consumption (W):

Input Voltage (V):

Output Voltage (V):

Battery Configuration:

Driver Included:

Electric Current:

2.5

220-240

20-90

LiFePo4

Yes

AC

Light Data

Frequency Range (Hz): 50/60

Environment

CE RoHS: Yes
IK Rating (Impact Protection): IK04
IP Rating (Ingress Protection): IP20
Lowest Operating Temperature (°C): 5
Maximum Operating Temperature (°C): 45

Packaging

Barcode: 5055788288862

Package Weight (g):250Package Length (mm):28Package Width (mm):240Package Depth (mm):50

Integral-led.com - Product Design And Specification Subject To Change Or Modification Without Notice. Image For Illustration Only. E&OE