



| <b>Technical Specification</b> |   |
|--------------------------------|---|
| <b>Manufacturer</b>            | Status International (UK) Ltd.  |
| <b>Address</b>                 | Unit 1, Whitehall 26 Business Park, Heathfield Lane, Birkenshaw, BD11 2HW |
| <b>Product</b>                 | Status 4 Way 2 Metre Extension Socket With Neon                           |
| <b>Product Code</b>            | 4WS2MCP20   |
| <b>Cable Length (Approx.)</b>  | 2 Metres  |
| <b>Number of Sockets</b>       | 4   |
| <b>Maximum Load</b>            | 13A   |
| <b>Mounting Type</b>           | Keyhole   |
| <b>Surge Protection</b>        | No  |

### Technical Specification

- 13 Amp – 220-240V ~ 50/60Hz
- Features safety shuttered sockets to prevent accidental access to live parts.
- Features Surge Protection to help protect valuable electronic equipment from spikes in surges in the electrical current.
- Features neon power indicator light.
- If the extension socket is damaged it cannot be repaired, it must be disposed of immediately.
- Ensure the cable does not cause a trip or snagging hazard.
- Do not connect this extension to another extension lead or cable reel.
- Do not remove the plug and connect direct to the mains power supply.
- Do not exceed the maximum loading (3120W, 13A).
- Take care not to damage the cable or fittings.
- Disconnect from the mains power supply when not in use.
- Do not use in damp or wet conditions.
- For indoor use only.



- Complies to BS1363/A, IEC61643-1.
- If in doubt, consult a qualified electrician.