

1.8m (6ft) Tail Call Lead

Part No. **NC805C/6**



Overview

A short 1.8m tail call lead for use with C-TEC's Quantec and 800 Series Call Systems.

Allows users to remotely generate Standard calls from armchairs, beds, etc.

Comprises a pear-shaped call push, 1.8m (6ft) trailing lead and a 6.35mm remote jack plug.

Easily connects to the 6.35mm remote socket on compatible Quantec and 800 Series call points.

Activating the pear push or removing the tail call lead from a call point's remote socket will generate a Standard call.

Technical Specifications

Compatibility	C-TEC's Quantec and 800 Series Call Systems.
Quiescent current	0mA (none).
Alarm current	Determined by the type of control equipment and number / type of field devices connected to the system.
Indicators	Reassurance LED on host call point will illuminate steady when call push is activated and/or removed.
Controls	Red Call button (generates a Standard call on activation when connected to a compatible Quantec or 800 Series call point).
Connections	6.35mm (quarter inch) jack plug.
Onboard Sounder	No.
Onboard Infrared Receiver	No.
Product dimensions (mm)	26 W x 21 H x 74 D mm (pear push). Lead is 1.8m (6ft) long.
Construction & finish	Plastic.
IP Rating	IP40.
Weight	64g
Operating conditions/temperature	-5°C to +40°C. Max. relative humidity 95% non-condensing.



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom